RS-900

Specification

Item


Condition Unit Limit Nominal

Roadshar = gelhard

32

Current drain Distortion	Frequency response	Min. noise level	Max. noise	Channel balance	Tone effect	Track crosstalk	Separation	S/N ratio	10% THD outpu	Output power	Take up torque	F.F. time	WOW/flutter	Tape speed	Cassette Tape Section:
MTT-112 MTT-118	onse MTT-117	MTT-501	MTT-501	MTT-118	MTT-113	MTT-121	MTT-141	MTT-112	10% THD output power MTT-112	MTT-112			MTT-111	MTT-111	ection:
R.O. 1KHz	125Hz 6.3KHz			1KHz	6,3KHz	1KHz	1KHz	1KHz	1KHz	1KHz		C-60	3KHz	3KHz	
% mA	ар В	3	₹ 	dВ	dВ	dВ	В	ВВ	٤	٤	GCM	SEC.	%	%	
6 000 3	(+ 1+ 080 O)	2	5	4	11-17	42	32	42	2	2.5	30-60	220	0.3	-1 -+3	
400 1.7	ጐ ጐ	_	70	0	15	46	36	46	2.2	ω	43	200	0.2	† 2	

Schematic Diagram AMP P.C.B **R113** 1ΚΩ D101: SIB- 01- 02 or W03C or SRIK- 4 IC1,IC2: TA7063p B.C.D or F14BP FINAL NUMBER R120,R201,C135 L101,D101,IC3 SW502,D201,VR3 SW501:POWER SW SW502:A/S SW D20!:GL-9PG2 IC I ,IC2: TA7063p B.C.D IC3 : TA7203p B.C.D MI : DC MOTOR



Parts List **RS-900** Mechanism

								NAME	ISSUED		
REF. NO.	PART NO.	DESCRIPTION	QTY	ORDER Q'TY	REMARK	, REF.	PART NO.	DESCRIPTION	QTY	ORDER Q'TY	REMARK
1	0022018	Chassis Assembly	1			52	0026068	Screw P.H. M2.6 x 3	3		
2	0022027	Cassette Holder Assembly	1			53	0026771	Screw P.H.S. M2 x 6	1	*********	
3	0022036	Head Base Assembly	1	***************************************		54	0026123	Screw P.T. 2.6 x 4	3		
4	0022045	CP Plate Assembly	1	***************************************		55	0026132	Screw P.T. 2.6 x 5	1		
5	0022054	Control Lever Assembly	1			56	0026086	Screw B.H. M2x 5	2		
7	0022063	Lift Arm	1				0028795	Azimuth Screw	1		
8	0022072	Eject Lever	1	***************************************		57			1	***************************************	
9	0022341	Push Spring	1	***************************************		58	0026327		1	••••••	
10	0022009	Plain Washer 2 x 14 x 0.5t	1			59	0026724	E -Ring 1.5φ		***************************************	
11	0026715	Clutch Plate	1	***************************************		60	0026188	E-Ring 2φ	5	***************************************	
12	0020713	Bind Rug	2			61	0026197	E-Ring 3φ	5		
13	0021467	Azimuth Washer	1	***************************************		62	0029475	F-170D Mecha Assembly	1		
14	0023010	Motor Pulley	1								
		•	1								
15 16	0023141	Special Washer	1	***************************************							
16	0023021	Eject Lever Shaft	1	***************************************							
17	0023049	Roller	2								
18	0023076	Guide Roller A	1	•••••							
19	0023113	Guide Roller B	2	***************************************							
20	0023169	CP Flywheel	1								
21	0023196	Clutch Assembly (22,23, 45.4	17) 1								
22	0025019	Clutch Base	(1)								
23	0025028	Clutch Pulley	(1)								
24	0025037	Clutch Bush	(1)								
25	.0021633	FF Lock Lever	1								
26	0024117	Pintch Roller Assembly	1								
27	0024015	Driving Belt	1							•	
28	0024024	Clutch Belt	1								
29	0026706	Gear Unit	1								
30	0024042	Eject Spring	1	***************************************		Ì					
31	0024024	Head Base Spring	1	***************************************							
32	0024061	Clutch Spring	(1)								
33	0024071	Holder Spring	1								
34	0024089	Pintch Spring	1	••••••							
35	0024098	Azimuth Spring	1	***************************************							
36	0024000	Control Lever Spring	1								
37	0022504	FF Lock Spring	1	••••••							
38	0021033	Sanp Spring	1	•••••							
39	0026580	Tension Spring	1			1					
40	0026696	Reset Spring	1								
41	0026696	Motor	1	***********							
			1								
42	0026401	Head	1								
43	0021032	Leaf Switch LSC-1223	1								
44	0020991	Leaf Switch LSB-1123	1	•••••							
45	0026012	Felt $\phi 9 \times \phi 14 \times t1.0$	(1)								
46 '	0026020	Washer $\phi 2.2 \times \phi 4 \times t0.13$	1								
47	0026031	Washer $\phi 5.2 \times \phi 8 \times t0.25$	(1)	***************************************		1					
48	0026252	Nylon Washer $\phi 1.8 \times \phi 4 \times t 0.4$		***************************************							
49	0026012	Slust Packing	1			1					

ORDER NO.

ORDER NO.

Parts List **RS-900** General / Electrical

49

51

0026012

0026041

0026059

Slust Packing

Screw S.S. M2 x 4

Screw P.H. M2 x 3

				,			<u>N</u>	IAME	ISSUED		
REF. NO.	PART NO.	DESCRIPTION	Ω'ΤΥ	ORDER Q'TY	REMARK	REF. NO.	PART NO.	. DESCRIPTION	Q'TY	ORDER Q'TY	REMARK
101	0022091	Under	1			IC1,IC2	7773004	IC TA7063P	2		
102	0022101	Top Cover	1	• • • • • • • • • • • • • • • • • • • •		IC3	7773013	IC TA7203P	1		
106	ó026234	Volume Mask (R)	3			D101	7775501	Diode W03C or F-14BP or	1		
110	0025241	Slide Volume 10KΩ x 2 A	2					S1B-01-02			
111	0025259	Slide Volume 50KΩ G	1			L101	0021272	Choke Coil SCH-081	1		
112	0026059	Screw P.H. M2 x 3	6			C103,C104	7771099	Mylar Capacitor	2	,	
113	0026095	Screw P.H. M2.6 x 4	2					0.0022µF 50∨K			
114	0026105	Screw B.T. M3 x 5 Black	4			C129,C130	7771007	Mylar Capacitor	2		
115	0021541	DIN Power Connector	1					0.1μF 50VK			
116	0021476	DIN Speaker Connector (L)	1	*************************		C125,C126	7771060	Mylar Capacitor	2		
117	0021513	DIN Speaker Connector (R)	1					0.022μF 50VK			
118	0021522	Earth Terminal	1			C107,C108	7771052	Mylar Capacitor	2		
119	0021485	Coad Stopper Plate	1			'		0.0068µF 50VK			
122	0026132	Screw P.T. 2.6 x 5	10			C111,C112	7771071	Mylar Capacitor	2		
126	0023130	Dust Cover Shaft	(1)	***************************************				0.047μF 50VK			
127	0024108	Dust Cover Spring	(1)			C133	7770003	Elect Capacitor 470µ/16WV	1	.,,,,,,,,	
128	0025340	Volume Hanger (L)	1			C127,C128	7770012	Elect Capacitor 470µ/10WV	2	.,	
129	0025388	Volume Hanger (R)	1	,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,		C118	7770020	Elect Capacitor 33µ/16WV	1	,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,	
130	0025314	Dust Cover	(1)			C135,C134	7770031	Elect Capacitor 47µ/10WV	3	***************************************	
131	0025517	Nose Piece	(1)			C117		·			
132	0025367	VR Knob A	2	***************************************		C101,C102	7770041	Elect Capacitor 4.7µ/25WV	8	************	
133	0025295	VR Knob B	1			C109,C110		,			
134	0025332	Eiect Knob	1			C115,C116					
135	0025288	Led Green GL-9PG2	1			C119,C120					
	7773595	Carbon Resistor 330Ω 2W	1	***************************************		C105,C106	7770059	Elect Capacitor 10µF/16WV	2	********	
136		ERG-12ANJ331	,	•••••		C132,C131	7772001	Ceramic Capacitor 0.01µF	2	***************************************	
137	0026179	Screw P.H. with S.W. M2x4	1			C123,C124	7772011	Ceramic Capacitor 0.0022µF	2	*******	
138	0029373	Nose Piece Ass'y(126,127,130,13		***************************************		C113,C114	7772029	Ceramic Capacitor 330pF	2	,	
146	0026594	LED PCB	 1			C121,C122	7772038	Ceramic Capacitor 10pF	2	,	
151	0028011	Accessory Screw Kitts	1			R119	7774440	Carbon Resistor 10KΩ 1/8 PR	1	***************************************	
152	0028011	Side Hanger	2	•••••••		R117,R118	7774190	Carbon Resistor 3.3Ω 1/4 PR	2	***************************************	
153	0028121	Rear Hanger	1			R113,R114	7774395	Carbon Resistor 1KΩ 1/8 PR	2		
154	0023121	Spair Fuse 3A	1			R120	7774560	Carbon Resistor 5.6KΩ 1/8 PR	1		
156	0021671	DIN Power Cord	1			R109.R110	7774516	Carbon Resistor 12K Ω ¹ / ₈ PR	2		
	0021024	with Earth Coad	'			R101,R102	7774461	Carbon Resistor 18KΩ ½ PR	4		
168		Screw with s. wesher P.H.	(4)	***************************************		R105,R106		, •			
		M4×8	, . ,			R111,R112	7774618	Carbon Resistor 220K Ω ½ PR	6	**********	
159		Plain washer 4 ϕ	(4)			R115,R116		, ,			
160		Bolt M5x8	(1)			R103.R104					
161		Spring lock washer 5φ	(1)	***************************************		R107,R108	7774618	Carbon Resistor 470KΩ 1/8 PR	2		
162		Plain washer 5φ	(1)	••••••		'- '		70		***************************************	
163		Taping screw 6 ϕ x12	(3)		•	1					i
164		Spring lock washer 6φ	(3)	***************************************							
165		Plain washer 6ϕ	(3)	***************************************							
201	0029022	AMP Ass'y									
202	0029022	AMP P.C.B. F-100	(1)								,
202	0021504	Radiator 40402	1								
203		AMP Mounting Plate 40460	1	******************************							
204	0022156 0026114	•	1	***************************************							
206		Screw B.H. M2.6 x 6	2								
	0026140	Nut M2.6	2			1					